



ORDERING INFORMATION - CODE NUMBERING SYSTEM

Specify Complete Connector By Selecting An Option From Step 1 Through 8

STEP	1	2	3	4	5	6	7	8	9
EXAMPLE	SADD	15	S	S	G	M	S	D	
STEP 1 - BASIC SERIES SADD series									STEP 9 - SPECIAL OPTIONS SEE APPENDIX ON PAGE 95.
STEP 2 - CONNECTOR VARIANT 15, 26, 44, 62, 78, 104									STEP 8 - 2ND CONNECTOR HOUSING (SHELLS) OPTION G - Gold over copper plate. D - Gold over copper plate and dimpled (male connectors only).
STEP 3 - 1ST CONNECTOR GENDER *3 M - Male S - Female - PosiBand closed entry contacts, see page 1 for more information.									*1 STEP 8 - 2ND CONNECTOR MATING STYLE 0 - Swaged spacer 0.120 [3.05µ] mounting hole S - Swaged spacer 4-40 UNC-2B threads *2 E - Rotating male and female jackscrews (Select 0 in Step 7) *2 E6 - Rotating male and female polarized jackscrew (Select 0 in Step 7) *2 T - Fixed male and female jackscrews (Select 0 in Step 7) *2 T6 - Fixed male and female polarized jackscrew (Select 0 in Step 7)
*1 STEP 4 - 1ST CONNECTOR MATING STYLE 0 - Swaged spacer 0.120 [3.05µ] mounting hole S - Swaged spacer 4-40 UNC-2B threads *2 E - Rotating male and female jackscrews (Select 0 in Step 7) *2 E6 - Rotating male and female polarized jackscrew (Select 0 in Step 7) *2 T - Fixed male and female jackscrews (Select 0 in Step 7) *2 T6 - Fixed male and female polarized jackscrew (Select 0 in Step 7)									STEP 6 - 2ND CONNECTOR GENDER M - Male
STEP 5 - 1ST CONNECTOR HOUSING (SHELLS) OPTION G - Gold over copper plate. D - Gold over copper plate and dimpled (male connectors only).									NOTES *1 Connector mating style for both connectors must be the same if 0 or S is used. If E or E6 is used in either Step 4 or 8 the other step must be 0. *2 For hardware information, see page 64. *3 Male option available only on connector variant 78.

SADD SERIES

Do you need 2-D drawings or 3-D models?
See page 18 for more information!

POSITRONIC INDUSTRIES

Connector Excellence[®]

Connector Families

Power

D-SUBMINIATURE

Circular

RECTANGULAR

Hermetic

THERMOCOUPLE

POSITRONIC INDUSTRIES, INC.

423 N Campbell Avenue • PO Box 8247 • Springfield, MO 65801
Tel (417) 866-2322 • Fax (417) 866-4115 • Toll Free (800) 641-4054
info@connectpositronic.com

POSITRONIC INDUSTRIES, S.A.S.

Zone Industrielle d'Engachies • 46 Route d'Engachies
France 32020 Auch Cedex 9
Telephone 33 5 62 63 44 91 • Fax 33 5 62 63 51 17
contact@connectpositronic.com

POSITRONIC ASIA PTE LTD.

3014A Ubi Road 1 #07-01 • Singapore 408703
Telephone (65) 6842 1419 • Fax (65) 6842 1421
singapore@connectpositronic.com



POSITRONIC[®]
GLOBAL *Connector* SOLUTIONS

Quality Solutions
Reliable Service